

# RE716P1TLP( G ) Manual Pull Station



## Product Overview

RE-716P Manual Pull Station is a high quality non-toxic die-cast manual pull station. Low profile design and smooth edges offer an attractive yet functional design. All components are prepainted or have plated surfaces to inhibit corrosion. Electrically the RE-716P Manual pull station is unbeatable with 10 Amp snap action switch offered in all possible contact arrangements (including gold contacts). The RE-716P pull station can be used with or without a break glass rod with replacement requiring no special tools.

## Features

- Lift and pull
- Break glass cover
- Weather and Explosion proof versions
- All stations offer hex screw or key lock access.

## Construction Material

- Painted Die Cast Housing.
- 14 Ga plated steel black plate.
- Corrosion inhibited surfaces.
- Terminal block (4 Position)
- Single Gang Mounting
- 10 A , 120VAC snap action switch (S.P.S.T.)



## Specification

### Electrical

Switch : 10A@120VAC

### Dimensions

Station Width : 3.200 in  
Length : 4.750 in  
Depth : 0.875 in  
Weight : 15.5 oz / 420 grams  
Mount : Single gang

## Ordering Information

MODELS	DESCRIPTION	COLOR
RE716P1TLP( G )	Manual Pull station Dual Action	GREEN



### India:

**RAVEL ELECTRONICS PVT LTD.,**  
(An ISO 9001 Certified Company)  
150A, Electronics Industrial Estate, Perungudi, Chennai - 96 .India.  
E-Mail: [marketing@ravelfire.com](mailto:marketing@ravelfire.com); Web : [www.ravelfire.com](http://www.ravelfire.com)

### United Kingdom:

**RAVEL ELECTRONICS LTD.,**  
Unit 11, Chancel Industrial Estate, Newhall street,  
Willenhall WV13 1NX, West Midlands, United Kingdom.  
E-mail: [info@ravelfire.co.uk](mailto:info@ravelfire.co.uk) ;Web: [www.ravelfire.co.uk](http://www.ravelfire.co.uk)